



Volcano2000

Ultimate Jumping Power

The Volcano 2000 is a 2000A Peak Current jump-starter for 12V batteries on gas engines (up to 10.0L) and diesel engines (up to 8.0L). It also works as a power bank, charging your mobile devices up to 75% faster than a standard charger. With this multi-functional tool your smartphone's battery level can go from 0 to 80 percent in only 35 minutes. The Volcano 2000 offers a convenient way to always keep your devices topped off while being ready to jump-start at any time. With its rugged, shock-proof, and water-resistant enclosure, this on-the-go product is ideal for any climate, providing you safety and durability.

Features

- 20800 mAh Lithium Polymer Battery
- Wireless Charging for Smartphones
- 5V/2.1A and QC3.0 Outputs for Faster Charging
- IP65 Waterproof Rugged Enclosure
- Ideal for Cars, Trucks, Boats, Motorcycles, ATVs, Mowers, and More
- LED Flashlight With 3 Modes - Steady Light, SOS, and Strobe
- Protects against Short Circuit, Reverse Polarity, Over-Current, Over-Charge, and Over-Discharge

Comparison

Volcano 2000

- Jumpstarter and Power Bank
- Wirelessly Charges Devices
- Comes with an LED Flashlight

Volcano 2000 Pro

- Jumpstarter and Power Bank
- Smart Clamps With Built-in Protections for Extra Safety
- Wirelessly Charges Devices
- Comes with an LED Flashlight

Volcano 2000 Pro S

- Jumpstarter, Power Bank and Battery Tester
- Bluetooth-Enabled Smart Clamps
- Compatible with Phoenix Series of Scanners
- Wirelessly Charges Devices
- Comes with an LED Flashlight

Specs

- Type C Input: 5V/3A
- Type C Output: 5V/3A
- USB Output: 5V/2.1A
- DC Output: 12V/10A
- Working Temperature: -4°F to 158°F
- Over-Discharge Protection: 13V±0.5V
- Dimensions: 8.11*3.76*1.65 inches
- Weight: 2.98lb

What's in the Box



- Volcano 2000
- Heavy-Duty Copper Clamps
- Type C Cable
- DC to Cigarette Lighter Converter
- User Manual
- Carrying Bag